

CMOS BCD-to-Seven-Segment Latch/Decoder/Driver For Liquid-Crystal Displays


High-Voltage Types (20-Volt Rating)

Features:

- Display blanking of all illegal input combinations
- Latch storage of code
- Capability of driving two low power TTL loads, two HTL loads, or one low power Schottky load over the full rated-temperature range
- Pin-for-pin replacement for the CD4056B (with pin 7 tied to V_{SS})
- Direct LED driving capability

■ CD4543B is a BCD-to-seven segment latch/decoder/driver designed primarily for liquid-crystal display (LCD) applications. It is also capable of driving light emitting diode (LED), incandescent, gas-discharge, and fluorescent displays. This device is functionally similar to and serves as direct replacement for the CD4056B when pin 7 is connected to Vss. It differs from the CD4056B in that it has a display blanking capability instead of a level-shifting function and requires only one power supply. When the CD4056B is used in the level shifting mode, two power supplies are required. When the CD4543B is used for LCD applications, a square wave must be applied to the PHASE input and the backplane of the LCD device. For LED applications a logic 1 is required at the PHASE input for common-cathode devices; a logic 0 is required for commonanode devices (see truth table).

The CD4543B is supplied in 16-lead dual-in-line plastic packages (E suffix), 16-lead small-outline packages (M, M96, MT, and NSR suffixes), and 16-lead thin shrink small-outline packages (PW and PWR suffixes).



- 100% tested for guiescent current at 20 V
- Maximum input current of 1 µA at 18 V over full package-temperature range; 100 nA at 18 V and 25°C
- Noise margin (full package-temperature range)= 1 V at V_{DD}=5 V 2 V at V_{DD}=10 V 2.5 V at V_{DD}=15 V
- 5-V, 10-V, and 15-V parametric ratings
- Meets all requirements of JEDEC Tentative Standard No. 13B, "Standard Specifications for Description of 'B' Series CMOS Devices"

Applications:

- Instrument display driver
- Dashboard display driver
- Computer/calculator display driver
- Timing device driver (clocks, watches, timers)

MAXIMUM RATINGS, Absolute-Maximum Values:

DC SUPPLY-VOLTAGE RANGE, (V _{DD})	
Voltages referenced to VSS Terminal)	,0.5V to +20V
INPUT VOLTAGE RANGE, ALL INPUTS	0.5V to V _{DD} +0.5V
DC INPUT CURRENT, ANY ONE INPUT	
POWER DISSIPATION PER PACKAGE (PD):	
For TA = -55°C to +100°C	500mW
For T _A = +100°C to +125°C	Derate Linearity at 12mW/°C to 200mW
DEVICE DISSIPATION PER OUTPUT TRANSISTOR	
FOR TA = FULL PACKAGE-TEMPERATURE RANGE (All Package Types)	
OPERATING-TEMPERATURE RANGE (TA)	55°C to +125°C
STORAGE TEMPERATURE RANGE (Tstg)	65°C to +150°C
LEAD TEMPERATURE (DURING SOLDERING):	
At distance $1/16 \pm 1/32$ inch $(1.59 \pm 0.79$ mm) from case for 10s max	+265°C





Fig. 1 - BCD-to-seven-segment latch/decoder/driver CD4543B logic circuit diagram.


RECOMMENDED OPERATING CONDITIONS at TA=25°C, Unless Otherwise Specified
For maximum reliability, nominal operating conditions should be selected so that operation is always within the following ranges:

		Lin			
CHARACTERISTIC	V _{DD} (V)	MIN.	TYP.	UNITS	
Supply-Voltage Range (For TA=Full Package-Temperature Range)		3	- 18	V	
	5	250	125		
Latch Disable Pulse Width twh	10	100	50		
	15	80	40	1	
	5	60	15		
Minimum Data Setup Time tsu	10	20	-5	ns	
	15	10	-5	_	
	5	25	-5]	
Minimum Data Hold Time t _H	10	20	10	1	
	15	20	10		

STATIC ELECTRICAL CHARACTERISTICS

CUADAG	error and enter such as a second of the seco	CONDITIONS			LIMITS AT INDICATED TEMPERATURES (°C)							
CHARAC-		٧o	VIN	V			<u> </u>	1	+25			UNITS
		(V)	(V)	V _{DD}	-55	-40	+85	+125	Min.	Typ.	Max.)
Quiescent		-	0, 5	5	5	5	150	150	_	0.04	5	;
Device	1. mg	<u></u>	0,10	.10	10	10	300	300		0.04	10	μΑ
Current	IDD	12.1	0,15	15	20	20	600	600		0.04	20	
Max.			0,20	20	100	100	3000	3000	_	0.08	100	
Output Low (Sink)		0.4	0, 5	5	0.64	0.61	0.42	0.36	0.51	1	_	
Current	1	0.5	0,10	10	1.6	1.5	1.1	0.9	1.3	2.6		
Min.	IOL	1:.5	0,15	15	4.2	4	2.8	2.4	3.4	6.8		
Output High		4.6	0, 5	. 5	-0.46	-0.44	-0.30	-0.26	-0.37	-0.75	111-11	mA
(Source)		2.5	0, 5	5	-1.6	-1.5	-1.1	-0.9	-1.3	-2.6		1
Current	IOH"	9.5	0,10	10	-0.98	-0.92	-0.68	-0.55	-0.8	-1.6		
Min.		13.5	0,15,	15	-3.33	-3.18	-2.2	-1.9	-2.7	-5.4 °		
Output Voltage:	i i i i i i i i i i i i i i i i i i i	1	0, 5	5		0.0	05			0	0.05	
Low-Level	VOL		0,10	10		0.0	05		_	0	0.05	
Max.		-	0,15	15		0.6	05			0	0.05	
Output Voltage:		1	0, 5	5		4.	95		4.95	5		, V ,
High-Level	Voн		0,10	10	191	9.	95	8	9.95	10	_	100
Min.			0,15	15		14.95			14.95	15		
Input Low		0.5,4.5 — 5 1.5		* *;		_	1.5					
Voltage	٧١٢	1, 9	<u> 2 – </u>	10		3	3	-	_		3	
Max.		1.5,13.5	<u>, –</u>	15	1	4	<u>.</u>		_	_	4	.,
Input High		0.5,4.5	5,4.5 — 5	3.5		3.5		3.5	_	_	٧	
Voltage	VIН	1, 9		10		7			7		_	
Min.		1.5,13.5	<i>–</i>	15	11 11 -				_	_		
Input Current Max.	ΙΝ	_	0,18	18	±0.1	±0.1	±1	±1	<u>(</u> ™)	±10 ⁻⁵	±0.1	μΑ








Fig. 3 - Minimum output high (source) current characteristics.

DYNAMIC ELECTRICAL CHARACTERISTICS at TA=25°C; CL=50 pF, input tr,tf=20 ns, RL=200 kΩ

CHARACTERISTIC		TEST CONDITIONS		LIMITS All Packages			
		V _{DD} (V)	MIN.	TYP.	MAX.		
Propagation Delay Time	tPHL	5	_	600	1200		
		10	-	200	400		
		15	_	150	300		
		5	_	500	1000		
	^t PLH	10	-	200	400		
		15		150	300		
		5		180	360		
Transition Time	THL	10	-	90	180		
		15		65	130		
		5	[180	360	ns	
	tTLH	10	_	90	180		
		15		65	130		
		5	250	125	_		
Latch Disable Pulse Width	twH	- 10	100	50			
		15	80	40			
		5	60	15			
Address Setup Time	tsu	10	20	-5			
		15	10	-5			
		5	25	-5	_		
Address Hold Time	tH	10	20	10	-		
<u> </u>		15	20	10			
Input Capacitance	CIN	Any Input	_	5	7.5	pF	




Fig. 4 - BCD-to-seven-segment latch/decoder/driver functional diagram.




Fig. 5 - Typical output low (sink) current characteristics.




Fig. 6 - Minimum output low (sink) current characteristics.

TRUTH TABLE FOR CD4543B

	INPUT CODE OUTPUT STATE							OUTPUT STATE						
LD	ВІ	Ph*	D	С	В	, A	. a	b	С	d	•	f	9	DISPLAY
х	1	0	x	x	X	X	0	0	0	0	0	0	0	CHAR- ACTER
1	0	0	0	0	0	0	1	1	1	1	1	1	0	
1	l .			_		Table Tabl			l '			, i		1
1	0	0	0	0	0 '	1	0	1	1	0	0	0	0	
1	0	0	0	0	1	0	1	1	0	_1 :	1	0	1	E E
1	0	0	0	0	1	1	. 1	1.	1	1	0	0	1	;= <u> </u>
1	0	0	0	γ :1 4	0	0	0 .	1	. 1 ₂ 1 -1 ₂ -	. 0	0,	√ 1	1	Ц
1	0	0	0	1	0	1	1	0	1	1	0	1	1	5
1	0	0	0	1	1	0	1	. 0	1	1	1	1	10	5
1	0	0	0	1	1	1	1	1	1	0	0	0	0	
1	0	0	1	0	0	0	1	11	1	1	1	1	1	H
, 1 m	.0	0	1	0	0	1	1.	1	1	1	0	1	1	i i
1,33	0	0	1	0	1	0	0	0	0	0	0	0	0	Blank
1	0	0	1	0	1	1	0	0	0	0	0	0	0	Blank
1-	0	O	1	1	0	- 0	0	0	0	0	0	0	0	Blank
1	0	o	1	1 1	0	1	0	0	0	ا ہ ا	o	0	0	Blank
1	0	0	1	1	1	ا ہ ا	0	0	١٥	0	o	o	0	Blank
1	0	0	1 1	1	1	1	١٥	0	l٥	ا ہ	0	0	0	Blank
0	0	.0	X	X	X	X				: **	-	<u> </u>		asa in the gas
†	†	1		. <u> </u>	†			<u> </u>	Co	se of Combinat	ions			Display as above

X=Don't care.

^{**=}Depends upon the BCD code previously applied when LD=1.




Fig. 7 - Typical transition time as a function of load capacitance.




Fig. 8 - Typical propagation delay time as a function of load capacitance.

^{†=}Above combinations.

^{*=}For liquid-crystal readouts, apply a square wave to Ph.
For common cathode LED readouts, select Ph=0.
For common anode LED readouts, select Ph=1.




Fig. 9 - Typical dynamic power dissipation as a function of frequency.





Fig. 10 - Quiescent device current test circuit.

Fig. 11 - Input voltage test circuit.

Fig. 12 - Input current test circuit.




Dimensions and pad layout for CD4543BH.

Dimensions in parentheses are in millimeters and are derived from the basic inch dimensions as indicated. Grid graduations are in mils (10⁻³ inch).

N (R-PDIP-T**)

16 PINS SHOWN

PLASTIC DUAL-IN-LINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.


Falls within JEDEC MS-001, except 18 and 20 pin minimum body Irngth (Dim A).

The 20 pin end lead shoulder width is a vendor option, either half or full width.

D (R-PDSO-G**)

PLASTIC SMALL-OUTLINE PACKAGE

8 PINS SHOWN



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion, not to exceed 0.006 (0,15).

D. Falls within JEDEC MS-012

MECHANICAL DATA

NS (R-PDSO-G**)

14-PINS SHOWN

PLASTIC SMALL-OUTLINE PACKAGE



NOTES:

- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15.



PW (R-PDSO-G**)

14 PINS SHOWN

PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.

D. Falls within JEDEC MO-153

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments

Post Office Box 655303 Dallas, Texas 75265

Copyright © 2003, Texas Instruments Incorporated